



A low cost, proven service monitor for a variety of wireless communications test requirements

- FM and AM Signal Generators
- 2 μ V receiver for AM, FM and SSB
- Analog meters offer high visibility in all lighting conditions
- Paging test for analog paging formats and advanced digital paging with the AC510 option
- 0.2 ppm TCXO

Proven Performance

The FM/AM-500A is a communications service monitor that gives you the performance, field portability and durability you need in a value-priced and compact package.

Since its introduction, the FM/AM-500A has earned a loyal following among wireless testing professionals. It is an incredibly rugged and field-proven communication test set.

With proven performance, the FM/AM-500A is the perfect test solution for a wide range of wireless communication test requirements.

Typical applications include FM/AM testing, conventional two-way radio test, SSB testing and basic communication systems performance tests.

Standard Features

- FM and AM Signal Generator
- 2 μ V receiver for AM, FM and SSB
- 10 Hz to 9999.9 Hz variable audio generator and audio frequency error meter
- 1 kHz audio generator
- Frequency error meter with 1 Hz resolution

- Peak/Average watt meter
- Deviation measurement to 60 kHz
- SINAD/Distortion Meter
- 0.2 PPM TCXO
- Microphone input
- Audio demodulator output

Specification

RF Signal Generator

Frequency Range	250 kHz to 999.9999 MHz
Resolution	100 Hz
Variable Generate	Continuous tuning ± 10 kHz from selected frequency
Residual FM	< 100 Hz peak RMS
RF Output Power	-127 dBm to -20 dBm (10 dB steps with 11 dB range continuous vernier)
RF Output Accuracy	± 3 dB
Output Impedance	50 Ω Nominal
EXTERNAL MODULATION	
Frequency Response	FM: 2 Hz to 30 kHz (DC when in variable generate) AM: 10 Hz to 10 kHz (30% maximum modulation above 5 kHz)
Modulation Sensitivity	FM: 0.08 VRMS/kHz $\pm 30\%$ of reading AM: 0.01 VRMS/%
Distortion (1 kHz tone)	FM: <1% to 20 kHz deviation AM: <10% to 60% modulation
Input Impedance	Greater than 10 k Ω

FM/AM-500A Communications Service Monitor



Audio Generator

Operating Modes

Internal:	Modulation/Tone Out level controlled by 1 kHz or variable control
Speaker:	Tone applied directly to speaker with volume controlled by 1 kHz or variable control.
External + Internal:	External modulation input is summed directly with tones and applied to modulator

Tone Accuracy

Fixed:	Same as master oscillator
Variable:	$\pm 0.01\%$
Tone Distortion	(@ 2.5 VRMS Output)
Fixed	<0.5%
Variable	$\pm 0.5\%$ @ 1 kHz, <1.5% 10 Hz To 9999.9 Hz

Tone Output Level

0 to 2.5 VRMS into 150 Ω load

Frequency Range

10 Hz to 9999.9 Hz in 0.1 Hz increments

Generate Amplifier

Gain

30 dB ± 2 dB typical, 100 kHz to 1000 MHz

Test set output with amplifier installed

Variable to +10 dBm, FM and CW
Variable to +4 dBm, AM (nominal)

Power Meter

Range

0 to 15 and 0 to 150 watts peak or average responding

Accuracy

1 to 600 MHz:	$\pm 7\%$ reading $\pm 3\%$ full scale
600 to 1000 MHz:	$\pm 20\%$ reading $\pm 3\%$ full scale

Input Power

25 W continuous
150 W - 60 seconds on, 5 minutes off

FM/AM-500A

Receiver Monitor

Frequency Range

100 kHz to 999.9999 MHz in 100 Hz increments

Sensitivity

2 μ V (1 MHz to 1000 MHz, FM Narrow)

Demodulation Output Impedance

600 Ω

Frequency Error Meter

RF Accuracy

$\pm$ Master Oscillator, $\pm$ 3% of full scale

RF Ranges

$\pm$ 10 kHz, $\pm$ 3 kHz, $\pm$ 1 kHz, $\pm$ 300 Hz, $\pm$ 100 Hz, $\pm$ 30 Hz full scale.

Audio Counter Ranges

$\pm$ 300 Hz, $\pm$ 30 Hz, $\pm$ 3 Hz full scale

Audio Counter Accuracy

$\pm$ 0.01%, $\pm$ 6% of full scale

Modulation Meter

Type

Maximum of positive or negative peak (AM and FM)

FM Deviation Accuracy

$\pm$ 5% of reading, $\pm$ 3% of full scale

AM% Modulation Accuracy

$\pm$ 5% of reading, $\pm$ 3% of full scale

SINAD Distortion Meter

SINAD Range

3 to 20 dB @ 1kHz

Accuracy

$\pm$ 1 dB at 12 dB SINAD

Input Level

0.25 VRMS to 2 VRMS
(10 VRMS maximum SINAD)

Impedance

10 k Ω nominal

Distortion Range

0 to 20% at 1 kHz

General Characteristics

Dimensions

292 mm (11.5 in) wide, 124 mm (4.9 in) high,
363 mm (14.3 in) deep

Weight

9.9 kg (22 lb) with battery

Versions and Accessories

When ordering please quote the full order number information

Ordering Numbers

500A-110	FM/AM-500A, 110 VAC operation
500A-110-C	FM/AM-500A, 110 VAC, with Certificate of Calibration
500A-220	FM/AM-500A, 220 VAC operation
500A-220-C	FM/AM-500A, 220 VAC operation, with Certificate of Calibration
500A-T-110	FM/AM-500A, 110 VAC, with 0.05 ppm OCXO time base
500A-T-110-C	FM/AM-500A-T-110, with Certificate of Calibration
500A-T-220	FM/AM-500A, 220 VAC, 0.05 ppm OCXO timebase
500A-T-220-C	FM/AM-500A-T-220, with Certificate of Calibration
Accessories	
AC0005	Soft Padded Carrying Case
AC510	Paging Encoder
AC1201	Telescopic antenna
AC1205	Microphone
AC5201	Maintenance Manual
AC5249	Generate Amplifier +30 dB gain



IFR Americas, Inc., 10200 West York Street, Wichita, Kansas
67215-8999, USA. E-mail: info@ifrsys.com
Tel: +1 316 522 4981 Toll Free USA: 1 800 835 2352 Fax: +1 316 522 1360

IFR Ltd, Longacres House, Norton Green Road, Stevenage, Herts
SG1 2BA, United Kingdom. E-mail: info@ifrinternational.co.uk
Tel: +44 (0) 1438 742200 Freephone UK: 0800 282 388 Fax: +44 (0) 1438 727601

As we are always seeking to improve our products, the information in this document gives only a general indication of the product capacity, performance and suitability, none of which shall form part of any contract. We reserve the right to make design changes without notice. All trademarks are acknowledged. Parent Company IFR Systems, Inc. © IFR Ltd. 1999.

