



# Agilent 6680A Series Single-Output, 5000 W DC Power Supplies, GPIB

## Data Sheet

Reliable DC power for manufacturing test and long-term burn-in



- Low output ripple and noise
- Selectable compensation for inductive loads
- Analog control of output voltage and current
- Fan-speed control to minimize acoustic noise
- Built-in measurements and advanced programmable features
- Protection features to ensure DUT safety

This series of 5000 watt DC power supplies has the exceptional, proven reliability that test system engineers look for. It also has the features needed for easy test system integration.

Programming of the DC output and the extensive protection features can be done either from the front panel or using industry standard SCPI commands via the GPIB. Using the serial link, up to 16 power supplies can be connected through one GPIB address. Test system integration can be further simplified by using the *VXIplug&play* drivers.

The output voltage and current can also be controlled with analog signals. This is helpful for certain types of noisy environments, and also immediate reactions to process changes.

The 6680A series has extremely low ripple and noise for a 5000 watt DC power supply. This helps the built-in measurement system make extremely accurate current and voltage measurements.

Selectable compensation is provided for problem-free powering of inductive loads.



**Agilent Technologies**

## Specifications

<b>Specifications</b> (at 0 ° to 55 °C unless otherwise specified)	<b>6680A</b>	<b>6681A</b>	<b>6682A</b>	<b>6683A</b>	<b>6684A</b>	<b>6680A-J04</b> Special order option
<b>Number of outputs</b>	1	1	1	1	1	1
<b>GPIO</b>	Yes	Yes	Yes	Yes	Yes	Yes
<b>Output ratings</b>						
Voltage	0 to 5 V	0 to 8 V	0 to 21 V	0 to 32 V	0 to 40 V	0 to 3.3 V
Current (40 °C then derate linearly 1%/°C from 40 °C to 55 °C)	0 to 875 A	0 to 580 A	0 to 240 A	0 to 160 A	0 to 128 A	0 to 1000 A
<b>Programming accuracy</b> at 25 °C ± 5 °C						
Voltage 0.04% +	5 mV	8 mV	21 mV	32 mV	40 mV	5 mV
Current 0.1% +	450 mA	300 mA	125 mA	85 mA	65 mA	450 mA
<b>Ripple and noise constant voltage mode</b> from 20 Hz to 20 MHz						
Voltage rms	1.5 mV	1.5 mV	1.5 mV	1.0 mV	1.0 mV	3.4 mV
peak-to-peak	10 mV	10 mV	10 mV	10 mV	10 mV	15 mV
<b>Readback accuracy</b> at 25 °C ± 5 °C (percent of reading plus fixed)						
Voltage 0.05% +	7.5 mV	12 mV	32 mV	48 mV	60 mV	7.5 mV
Current 0.1% +	600 mA	400 mA	165 mA	110 mA	90 mA	600 mA
<b>Load and line regulation</b>						
Voltage 0.002% +	0.19 mV	0.3 mV	0.65 mV	1.1 mV	1.5 mV	0.19 mV
Current 0.005% +	65 mA	40 mA	17 mA	12 mA	9 mA	77 mA
<b>Transient response time</b>	Less than 900 μs for the output voltage to recover to within 150 mV following a change in load from 100% to 50% or 50% to 100% of the output current rating of the supply					

<b>Supplemental characteristics</b> (Non-warranted characteristics determined by design and useful in applying the product)	<b>6680A</b>	<b>6681A</b>	<b>6682A</b>	<b>6683A</b>	<b>6684A</b>	<b>6680A-J04</b> Special order option
<b>Ripple and noise constant current mode</b> from 20 Hz to 20 MHz						
Current rms	290 mA	190 mA	40 mA	28 mA	23 mA	—
<b>Average programming resolution</b>						
Voltage	1.35 mV	2.15 mV	5.7 mV	8.6 mV	10.8 mV	12 mV
Current	235 mA	155 mA	64 mA	43 mA	34 mA	260 mA
OVP	30 mV	45 mV	120 mV	180 mV	225 mV	25 mV
<b>Output voltage programming response time*</b> (excluding command processing time)	9 ms	12 ms	45 ms	60 ms	60 ms	9 ms
<b>Output common-mode noise current</b> (to signal-ground binding post)						
rms	1.5 mA	1.5 mA	3 mA	3 mA	3 mA	2.0 mA
peak-to-peak	10 mA	10 mA	20 mA	20 mA	20 mA	12.5 mA

\* Full load programming rise/fall time (10% to 90% or 90% to 10%) with full resistive load equal to rated output voltage/rated output current.



## Ordering information

The 6680A power supplies come with full documentation on CD-ROM. The CD-ROM includes user's guide, programming guide, service manual, quick start guide, and application notes.

**Opt 208** 180 to 235 VAC, 3 phase, 47 to 63 Hz

**Opt 400** 360 to 440 VAC, 3 phase, 47 to 63 Hz

**Opt 602** Two bus bar spacers for paralleling power supplies (p/n 5060-3514)

**Opt 0L1** Printed user's and programming guides

**Opt 0B3** Printed service manual

## Accessories

**1CM028A\*** Rack mount flange kit 88.1 mm H (3U) and 132.6 mm H (2U) – 4 brackets (5U total)

**1CP014A\*** Double rack mount flange and handle kit 88.1 mm H (2U) and 132.6 mm H (3U)

**E3663AC** Support rails for Agilent rack cabinets

**p/n 5080-2148** Serial link cable 2 m (6.6 ft.)

**p/n 5060-3513** Three 30 A replacement fuses for 180 to 235 VAC line

**p/n 5060-3512** Three 16 A replacement fuses for 360 to 440 VAC line

## Application notes

*6671A/72A/81A/82A/90A System DC Power Supplies Product Overview*  
5988-3050EN

*Agilent DC Power Supplies for Base Station Testing*, 5988-2386EN

*10 Practical Tips You Need to Know About Your Power Products*,  
5965-8239E

\* Support rails required



Agilent Advantage Services is committed to your success throughout your equipment's lifetime. To keep you competitive, we continually invest in tools and processes that speed up calibration and repair and reduce your cost of ownership. You can also use Infoline Web Services to manage equipment and services more effectively. By sharing our measurement and service expertise, we help you create the products that change our world.

[www.agilent.com/find/advantageservices](http://www.agilent.com/find/advantageservices)



## Agilent Email Updates

[www.agilent.com/find/emailupdates](http://www.agilent.com/find/emailupdates)

Get the latest information on the products and applications you select.

## Agilent Channel Partners

[www.agilent.com/find/channelpartners](http://www.agilent.com/find/channelpartners)

Get the best of both worlds: Agilent's measurement expertise and product breadth, combined with channel partner convenience.

For more information on Agilent Technologies' products, applications or services, please contact your local Agilent office. The complete list is available at:  
[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)

## Americas

Canada	(877) 894 4414
Brazil	(11) 4197 3600
Mexico	01800 5064 800
United States	(800) 829 4444

## Asia Pacific

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 112 929
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Other AP Countries	(65) 375 8100

## Europe & Middle East

Belgium	32 (0) 2 404 93 40
Denmark	45 45 80 12 15
Finland	358 (0) 10 855 2100
France	0825 010 700*
	*0.125 €/minute
Germany	49 (0) 7031 464 6333
Ireland	1890 924 204
Israel	972-3-9288-504/544
Italy	39 02 92 60 8484
Netherlands	31 (0) 20 547 2111
Spain	34 (91) 631 3300
Sweden	0200-88 22 55
United Kingdom	44 (0) 118 927 6201

For other unlisted countries:

[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)

Revised: January 6, 2012

Product specifications and descriptions in this document subject to change without notice.

© Agilent Technologies, Inc. 2012  
Published in USA, March 14, 2012  
5990-9307EN

