

# Agilent 4263B LCR Meter 100 Hz to 100 kHz

## Technical Overview

### Introduction

The Agilent Technologies LCR meter makes fast measurements on components. It is optimized for applications that require precision and versatility. The instrument's performance ranges from general bench-top impedance measurements to complex transformer, coil and electrolytic capacitor measurements. The LCR meter offers fast, reliable, and versatile testing at a low cost.

### Satisfy your needs for...

#### Fast system test throughput

- Maximize testing with rapid 25 ms measurements
- Minimize user intervention with pass/fail testing
- Communicate results with display and GPIB
- Automate testing with built-in handler interface




#### Fault-free results

- Test with confidence using contact check function
- Remove parasitics with error correction
- Get the best data with 0.1% basic accuracy
- Eliminate trigger timing errors with trigger delay function

#### Versatile measurements

- Select from 11 impedance parameters
- Add three complex transformer parameters with Option 4263B-001
- Set signal level with 5 mVrms resolution
- Monitor actual ac voltage and current levels
- Pick from many test fixtures and accessories
- Save and recall up to ten measurement setups





**Key Parameters and Specifications**

**Test frequencies:**  
100 Hz, 120 Hz, 1 kHz, 10 kHz, 100 kHz

Option 4263B-002 adds 20 kHz

**AC test signal levels:**  
20 m-1 Vrms, 5 mVrms steps

**Basic accuracy:**  
0.1%

**Impedance parameters:**  
 $|Z|$ , R, X,  $|Y|$ , G, B, C, L, D, Q, U

Option 4263B-001 adds transformer measurement functions: turns-ratio, mutual-inductance and dc-resistance

**Cable length settings:**  
0, 1, 2, 4 meters

**Bias:**  
1.5 and 2.0 Vdc

**Error correction:**  
Open, short, and load

**Built-in system features:**  
GPIB and handler interfaces

**Measurement time (typical):**  
25 ms at best conditions

**Contact check time (typical):**  
5 ms per measurement

### High-quality results

- See five digits of data
- Make precise measurements with 0.1% basic accuracy
- Select from 11 impedance parameters
- Verify device performance at simulated operating conditions
- Monitor actual test signal voltage and current levels



Make reliable impedance measurements.

### System features for test automation


- Maximize accuracy with error correction
- Use performance specified with 0, 1, 2, and 4 meter cables
- Test device contact failure with contact check function
- Automate testing with GPIB interface
- Reduce ground-loops with isolated handler interface
- Continue testing after ac power loss with continuous memory
- Perform pass/fail testing with comparator function (High/In/Low)



The 4263B LCR meter is designed for automated applications.

### Evaluate transformers and coils with Option 4263B-001

- Measure turns-ratio, mutual inductance and dc-resistance
- Easily make connections with 16060A transformer test fixture
- Measure parameter responses with variable signal levels



Simplify transformer testing.

### Make electrolytic capacitor measurements

- Obtain versatile testing with a large capacitance range
- Keep costs down with built-in dc bias source
- Protect your investment: high energy protection on terminals
- Increase test throughput with fast system measurements
- Make reliable handler measurements with contact check function



Quickly evaluate electrolytic capacitors.

# Specifications

## Measurement accuracy




Figure 1. Conversion diagram

0.85 + $2.9 \times 10^{-8} Z_{ml}$	0.15 + $2.9 \times 10^{-8} Z_{ml}$	0.1 + $5.6 \times 10^{-8} Z_{ml}$	0.48 + $3.8 \times 10^{-7} Z_{ml}$	1.9 + $7.7 \times 10^{-7} Z_{ml}$	Accuracy not specified
0.85 + $2 \times 10^{-7} Z_{ml}$	0.15 + $2 \times 10^{-7} Z_{ml}$	0.095 + $1.4 \times 10^{-7} Z_{ml}$	0.36 + $5.1 \times 10^{-7} Z_{ml}$	1.4 + $1 \times 10^{-6} Z_{ml}$	1.2 + $1.4 \times 10^{-5} Z_{ml}$
0.85 + $2 \times 10^{-6} Z_{ml}$	0.15 + $2 \times 10^{-6} Z_{ml}$	0.09 + $1 \times 10^{-6} Z_{ml}$	0.16 + $1.9 \times 10^{-6} Z_{ml}$	0.8 + $3.7 \times 10^{-6} Z_{ml}$	
0.85 + $2 \times 10^{-5} Z_{ml}$	0.15 + $2 \times 10^{-5} Z_{ml}$	0.09 + $1 \times 10^{-5} Z_{ml}$	0.16 + $1.5 \times 10^{-5} Z_{ml}$	0.7 + $3.1 \times 10^{-5} Z_{ml}$	1.1 + $1 \times 10^{-4} Z_{ml}$
0.85 + $2 \times 10^{-4} Z_{ml}$	0.15 + $2 \times 10^{-4} Z_{ml}$	0.09 + $1 \times 10^{-4} Z_{ml}$	0.16 + $1.5 \times 10^{-4} Z_{ml}$	0.7 + $3 \times 10^{-4} Z_{ml}$	1.1 + $1 \times 10^{-3} Z_{ml}$
0.85 + $2 / Z_{ml}$	0.15 + $2 / Z_{ml}$	0.09 + $1 / Z_{ml}$	0.16 + $1.5 / Z_{ml}$	0.5 + $3.1 / Z_{ml}$	0.83 + $10 / Z_{ml}$
0.85 + $0.2 / Z_{ml}$	0.17 + $0.22 / Z_{ml}$	0.12 + $0.1 / Z_{ml}$	0.2 + $0.18 / Z_{ml}$	0.6 + $0.35 / Z_{ml}$	0.97 + $1.3 / Z_{ml}$
0.85 + $0.022 / Z_{ml}$	0.4 + $0.022 / Z_{ml}$	0.4 + $0.015 / Z_{ml}$	0.4 + $0.04 / Z_{ml}$	0.6 + $0.08 / Z_{ml}$	0.97 + $0.35 / Z_{ml}$
0.85 + $0.012 / Z_{ml}$	0.4 + $0.012 / Z_{ml}$	0.4 + $0.0075 / Z_{ml}$	0.4 + $0.028 / Z_{ml}$	0.6 + $0.056 / Z_{ml}$	0.97 + $0.26 / Z_{ml}$
DC	100 / 120	1k	10k	20k (Option 002 only)	100k

Table 1. Measurement accuracy ( $\pm\%$  of reading)

## Measurement conditions

1. Warm-up time:  $\geq 15$  min.
2. Ambient temperature:  $23 \pm 5$  °C
3. Test signal voltage: 1 Vrms
4. Test cable length: 0 meter
5. Open and short corrections performed
6. Measurement time: Medium or Long  
(Other test condition data is available in the operation manual.)

For |Z|, |Y|, L, C, R, X, G, and B accuracy (Ae), refer to Table 1. Table 1 equations yield accuracy based on frequency and DUT characteristic impedance (Zm). Zm is from Figure 1, Conversion Diagram.

$$D \text{ accuracy}(De) = \pm Ae/100$$

$$Q \text{ accuracy}(Qe) = \pm \frac{(Qm)^2 \times De}{1 - / + (Qm \times De)}$$

$$u \text{ accuracy}(ue) = 0.573 \times Ae$$

Ae = Accuracy of |Z|, |Y|, L, C, R, X, G, and B

De = D accuracy

Dm = Measured value of D

Qe = Q accuracy

Qm = Measured value of Q

ue = u phase angle accuracy

Zm = DUT impedance at test frequency in Hertz

## Other Specifications

### Measurement parameters/ranges

Parameter	Range
Z , R, X	1 m $\Omega$ to 100 M $\Omega$
Y , G, B	10 nS to 1000S
C	1 pF to 1 F
L	10 nH to 100 kH
D	0.0001 to 9.9999
Q	0.1 to 9999.9
u	-180° to +180°
$\Delta$	-999.99% to 999.99%

**Option 4263B-001:** DC resistance 1 m $\Omega$  to 100 M $\Omega$

Mutual inductance 1  $\mu$ H to 100 H (typical)

Turns-ratio 0.9 to 200 (typical)

### Measurement conditions and functions

**Test frequency:** 100 Hz, 120 Hz, 1 kHz, 10 kHz, 100 kHz. (Option 4263B-002 adds 20 kHz.)

**AC test signal level:** 20 m - 1 Vrms, 5 mVrms steps

**Bias:**

Internal: +1.5 and +2.0 Vdc

External: 0 to +3.0 Vdc

**Ranging:** Auto and Hold

**Trigger:** Internal, Manual, and External

**Trigger delay time:** 0 to 9999 ms in 1 ms steps

**Test cable lengths:**

0, 1 meter @  $f \leq 100$  kHz

2 meter @  $f \leq 10$  kHz (20 kHz)

4 meter @  $f \leq 1$  kHz

**Measurement time:**

SHORT	MEDIUM	LONG
25 ms	65 ms	500 ms

## Other instrument functions

**Test signal level monitor:**

Voltage, current

**Error Correction:** Open, Short, Load

**Comparator:** HIGH, IN, and LOW for each displayed parameter

**Save/recall:** 10 instrument states from non-volatile memory

**Front-end Protection:**

$$V_{max} = \sqrt{8/C} \quad @ \quad V_{max} \leq 250 \text{ V}$$

$$V_{max} = \sqrt{2/C} \quad @ \quad V_{max} \leq 1000 \text{ V}$$

C in Farads

**Handler interface:** Negative logic and isolated.

Signals are HIGH/IN/LOW, No-Contact, EOM, Index, Alarm, Keylock, Ext. Trigger.

**GPIB interface:** Instrument control, TALK-only mode for LISTEN-only printers using GPIB or Centronics/GPIB converter

### Physical characteristics

Power: 90-132 Vac or 198-264 Vac. 47-66 Hz. 45 VA typical.

**Operating temperature:** 0 to 45 °C


**Dimensions:** 320 (W) x 100 (H) x 300 (H) mm

**Weight:** 4.5 kg (typical)

## Test Fixtures/Accessories for the Agilent 4263B



**16060A transformer test fixture**  
Allows fast connections to transformers



**16065C external bias adapter**  
For external dc bias of DUT.  $V_{max} \leq 40$  Vdc.




**16089C Kelvin IC clip leads**  
IC package clip. 1 meter length.



**16089A Kelvin clip leads**  
Large clip. 1 meter length.

**16089B Kelvin clip leads**  
Medium clip. 1 meter length.

**16089D Alligator clip leads**  
Four clips. 1 meter length.



**16034G Test fixture**  
For SMD components.

Component dimensions (L x W):  
0.6 mm x 0.3 mm to 5.0. mm x 1.6 mm

## Ordering information <sup>1</sup>

### Agilent 4263B LCR Meter

Furnished accessory: power cable

#### Options

4263B-001 Add N/M/DCR Measurement Function

4263B-002 Add 20 kHz Test Frequency  
Test fixtures are not furnished as standard.

#### Manual options <sup>2</sup>

4263B-ABA U.S. - English localization

4263B-ABJ Japan - Japanese localization

4263B-0BW Add service manual

#### Cabinet options

4263B-1CM Rackmount kit

4263B-1CN Handle kit  
(Rack flange and handle kit are not compatible.)

#### Calibration certificate option

4263B-1A7 ISO 17025 compliant calibration

## Test fixtures and accessories

**16034E/G/H** SMD component test fixture

**16043-60011/12** 3-terminal SMD test fixture

**16044A** <sup>3</sup> Test fixture

#### Options

**16044A-ABA** U.S. - English localization

**16044A-ABJ** Japan - Japanese localization

**16047A/E** <sup>3</sup> Axial and radial test fixture

#### Options

**16047E-ABA** U.S. - English localization

**16047E-ABJ** Japan - Japanese localization

**16334A** SMD tweezer test fixture

**16048A** 0.94-meter/BNC test leads

**16048-60030** 0.94-meter/SMC test leads

**16048D** 1.89-meter/BNC test leads

**16048E** 3.8-meter/BNC test leads

**16060A** Transformer test fixture

**16065A** 200-Vdc external voltage bias fixture

**16065C** 40-Vdc external voltage bias adapter

**16089A** Large Kelvin clip leads

**16089B** Medium Kelvin clip leads

**16089C** Kelvin IC clip leads

**16089D** Alligator clip leads

**16089E** Kelvin clip leads

<sup>1</sup> Accessories and options are priced individually.

<sup>2</sup> Manual is not furnished as standard

<sup>3</sup> Must specify one of language options (ABA or ABJ) for operation manual of 16047E for shipment with product.

## Web Resource

[www.agilent.com/find/lcrmeters](http://www.agilent.com/find/lcrmeters)



### Agilent Email Updates

[www.agilent.com/find/emailupdates](http://www.agilent.com/find/emailupdates)

Get the latest information on the products and applications you select.



### Agilent Direct

[www.agilent.com/find/agilentdirect](http://www.agilent.com/find/agilentdirect)

Quickly choose and use your test equipment solutions with confidence.

## Remove all doubt

Our repair and calibration services will get your equipment back to you, performing like new, when promised. You will get full value out of your Agilent equipment throughout its lifetime. Your equipment will be serviced by Agilent-trained technicians using the latest factory calibration procedures, automated repair diagnostics and genuine parts. You will always have the utmost confidence in your measurements.

Agilent offers a wide range of additional expert test and measurement services for your equipment, including initial start-up assistance onsite education and training, as well as design, system integration, and project management.

For more information on repair and calibration services, go to

[www.agilent.com/find/removealldoubt](http://www.agilent.com/find/removealldoubt)

## www.agilent.com

For more information on Agilent Technologies' products, applications or services, please contact your local Agilent office. The complete list is available at:

[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)

### Americas

Canada	(877) 894-4414
Latin America	305 269 7500
United States	(800) 829-4444

### Asia Pacific

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 112 929
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Thailand	1 800 226 008

### Europe & Middle East

Austria	0820 87 44 11
Belgium	32 (0)2 404 93 40
Denmark	45 70 13 15 15
Finland	358 (0)10 855 2100
France	0825 010 700*
	*0.125 €/minute
Germany	01805 24 6333**
	**0.14 €/minute
Ireland	1890 924 204
Israel	972-3-9288-504/544
Italy	39 02 92 60 8484
Netherlands	31 (0)20 547 2111
Spain	34 (91)631 3300
Sweden	0200-88 22 55
Switzerland	0800 80 53 53
United Kingdom	44 (0)118 9276201

Other European Countries:

[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)

Revised: March 27, 2008

Product specifications and descriptions in this document subject to change without notice.

© Agilent Technologies, Inc., 1995, 2000, 2003, 2004, 2008

Printed in USA, April 15, 2008  
5964-6181E



Agilent Technologies